

PROBLEM:

For each of the following sinusoidal signals, pick one of the representations below that defines *exactly* the same signal. Write your answer $x_1(t)$, $x_2(t)$, $x_3(t)$, $x_4(t)$, or $x_5(t)$, in the box next to each signal. In addition, write the complex amplitude (phasor) (X_k) of the sinusoid for each case in the space provided.

ANS = $2 \cos(8\pi t + 5\pi/3)$

$X_k =$

ANS = $2 \cos(8\pi t + 4\pi/3)$

$X_k =$

ANS = $e^{j2\pi/3} e^{j8\pi t} + e^{-j2\pi/3} e^{-j8\pi t}$

$X_k =$

ANS = $\Re \left\{ (1 + j\sqrt{3}) e^{j8\pi t} \right\}$

$X_k =$

ANS = $2 \cos(8\pi t + 7\pi/3)$

$X_k =$

POSSIBLE ANSWERS: Some of these answers can be used more than once.

If one answer is used twice, another one won't be used at all.

1. $x_1(t) = \cos(8\pi t + 5\pi/3)$

2. $x_2(t) = \Re \left\{ 2e^{-j5\pi/3} e^{j8\pi t} \right\}$

3. $x_3(t) = 2 \cos(8\pi t - 4\pi/3)$

4. $x_4(t) = \Re \left\{ (-1 - j\sqrt{3}) e^{j8\pi t} \right\}$

5. $x_5(t) = e^{j5\pi/3} e^{j8\pi t} + e^{-j5\pi/3} e^{-j8\pi t}$