

PROBLEM:

Let $x(t) = 3.14 \cos(2200\pi t - \pi/3)$. In each of the following the discrete-time signal $x[n]$ is obtained by sampling $x(t)$ at a rate f_s ; and the resultant $x[n]$ can be written:

$$x[n] = A \cos(\hat{\omega}_0 n + \phi)$$

So for each part below, determine the values of A , ϕ and ω_0 . In addition, state whether or not the signal has been oversampled or undersampled.

- (a) Let the sampling frequency be $f_s = 1300$ samples/sec.
- (b) Let the sampling frequency be $f_s = 2500$ samples/sec.
- (c) Let the sampling frequency be $f_s = 6500$ samples/sec.