

PROBLEM:

Define a discrete-time signal via the formula:

$$y[n] = A \cos(0.16\pi n + \phi) \quad \text{for } n \geq 0$$

- Design a feedback filter that will synthesize $y[n]$. Give your answer in the form of a difference equation with numerical values for the coefficients. Assume that the synthesis will be accomplished by using an impulse input to “start” the difference equation (which has zero initial conditions).
- Determine the pole locations for the system function $H(z)$ that will synthesize $y[n]$.
- If this signal is played out through a D-A converter with $f_s = 8000$ Hz, what frequency will be heard?