

**PROBLEM:**

A proposed D-to-C converter takes a sequence  $y[n]$  as input and produces a continuous-time output  $y(t)$  according to the relation

$$y(t) = \sum_{n=-\infty}^{\infty} y[n]p(t - nT_s)$$

where  $T_s = 10^{-3}$  sec. The input sequence is given by the formula

$$y[n] = \begin{cases} \frac{1}{5}(n+1) & 0 \leq n \leq 4 \\ (0.5)^{n-4} & 5 \leq n \leq 9 \\ 0 & \text{otherwise} \end{cases}$$

- (a) Plot  $y[n]$  versus  $n$ .  
(b) For the pulse shape

$$p(t) = \begin{cases} 1 & -0.5 \times 10^{-3} \leq t \leq 0.5 \times 10^{-3} \\ 0 & \text{otherwise} \end{cases}$$

plot the output waveform  $y(t)$  over its non-zero region.

- (c) For the pulse shape

$$p(t) = \begin{cases} 1 - 1000|t| & -10^{-3} \leq t \leq 10^{-3} \\ 0 & \text{otherwise} \end{cases}$$

plot the output waveform  $y(t)$  over its non-zero region.