

**PROBLEM:**

Circle the correct answer to each of these short answer questions:

1. If the impulse response of an FIR filter is defined with a scaling parameter  $\beta$

$$h[n] = \beta(2\delta[n] - \delta[n - 1] + 2\delta[n - 2])$$

Determine  $\beta$  so that the DC value of the frequency response  $H(e^{j\hat{\omega}})$  will be equal to one.

- (a)  $\beta = 1$
- (b)  $\beta = 1/2$
- (c)  $\beta = 1/3$
- (d)  $\beta = 1/4$
- (e)  $\beta = 1/5$

2. For the following MATLAB code: `yy = firfilt( [1,0,0,0,-5], xx )` pick the correct difference equation for the filter being implemented.

- (a)  $y[n] = \delta[n] - 5\delta[n - 1]$
- (b)  $y[n] = \delta[n] - 5\delta[n - 4]$
- (c)  $y[n] = x[n] - 5x[n - 1]$
- (d)  $y[n] = x[n - 4]$
- (e)  $y[n] = x[n] - 5x[n - 4]$

3. The MATLAB statement: `xx = [ cos(0.13*pi*(0:2000)), cos(0.17*pi*(0:2000)) ] ;`

- (a) Defines `xx` as the sum of two sinusoids played simultaneously.
- (b) Defines `xx` as the concatenation of two sinusoids played in succession.
- (c) Defines `xx` as a frequency response.
- (d) Defines `xx` as a spectrogram.

4. If a filter is defined by the MATLAB operation: `yy = firfilt(0.2*ones(1,5),xx)`, then the filter is:

- (a) a highpass FIR filter.
- (b) a lowpass FIR filter.
- (c) a highpass IIR filter.
- (d) a lowpass IIR filter.
- (e) an allpass filter, i.e., its frequency response magnitude is constant.