

PROBLEM:

Solve for the unknown sinusoid in the following equation:

$$A \cos(\omega_0 t + \phi) + 2 \cos(\frac{1}{4}\pi t + 5\pi/6) = 2 \cos(\frac{1}{4}\pi(t + 12)) + \frac{1}{2} \cos(\frac{1}{4}\pi(t - 10))$$

- (a) Express your answer in the form $x(t) = A \cos(\omega_0 t + \phi)$ by finding the numerical values of A and ϕ , as well as ω_0 (give the correct units).
- (b) Make **TWO** complex plane plots to illustrate how complex amplitudes (phasors) are combined via vector addition to solve part (a). On the first plot, show a “head-to-tail” vector plot of the two complex amplitudes whose values are given by the sinusoids on the **left** side of the equal sign; on the second plot, show a “head-to-tail” vector plot of the two complex amplitudes for the sinusoids on the **right** side of the equal sign.