## PROBLEM:

Define x(t) as

(a) Use phasor addition to express x(t) in the form  $x(t) = A\cos(\omega_0 t + \phi)$  by finding the numerical values of A and  $\phi$ , as well as  $\omega_0$ .

 $x(t) = 5\cos(2\pi t + 5\pi/6) + 5\cos(2\pi(t - 0.25))$ 

(b) Make two complex plane plots to illustrate how complex amplitudes (phasors) were used to solve part (a). On the first plot, show the two complex amplitudes being added; on the second plot, show your solution as a vector and the addition of the two complex amplitudes as vectors (head-to-tail).

