

PROBLEM:

A signal $x(t)$ is periodic with period $T_0 = 8$. Therefore it can be represented as a Fourier series of the form

$$x(t) = \sum_{k=-\infty}^{\infty} a_k e^{j(2\pi/8)kt}.$$

It is known that the Fourier series coefficients for this representation of a particular signal $x(t)$ are given by the integral

$$a_k = \frac{1}{8} \int_{-4}^0 (4+t) e^{-j(2\pi/8)kt} dt. \quad (1)$$

- In the expression for a_k in Equation (1) above, the integral and its limits define the signal $x(t)$. Determine an equation for $x(t)$ that is valid over one period.
- Using your result from part (a), draw a plot of $x(t)$ over the range $-10 \leq t \leq 10$ seconds. Label it carefully.
- Determine a_0 , the DC value of $x(t)$.