

PROBLEM:

For each of the systems defined on the left, find the corresponding frequency response on the right. Pick the correct frequency response and enter the number in the answer box:

Impulse Response or Difference Equation**Frequency Response**

(a) $h[n] = (-\frac{1}{2})^n u[n]$

ANS =

(b) $h[n] = \delta[n] - (\frac{1}{2})^n u[n - 1]$

ANS =

(c) $h[n] = \delta[n] + \delta[n - 2]$

ANS =

(d) $y[n] = \frac{1}{2}y[n - 1] + x[n]$

ANS =

(e) $y[n] = \left((-\frac{1}{2})^n u[n] \right) * \left(\delta[n] + \delta[n - 1] \right)$

ANS =

1. $H(e^{j\hat{\omega}}) = \frac{1 + e^{-j\hat{\omega}}}{1 + \frac{1}{2}e^{-j\hat{\omega}}}$

2. $H(e^{j\hat{\omega}}) = 1 + \frac{1}{2}e^{-j\hat{\omega}}$

3. $H(e^{j\hat{\omega}}) = \frac{1 - e^{j\hat{\omega}}}{1 - \frac{1}{2}e^{-j\hat{\omega}}}$

4. $H(e^{j\hat{\omega}}) = \frac{1}{1 - \frac{1}{2}e^{-j\hat{\omega}}}$

5. $H(e^{j\hat{\omega}}) = 2e^{-j\hat{\omega}} \cos(\hat{\omega})$

6. $H(e^{j\hat{\omega}}) = 1 + e^{-j\hat{\omega}}$

7. $H(e^{j\hat{\omega}}) = \frac{1}{1 + \frac{1}{2}e^{-j\hat{\omega}}}$

8. $H(e^{j\hat{\omega}}) = \frac{1 + \frac{1}{2}e^{-j\hat{\omega}}}{1 + e^{-j\hat{\omega}}}$